

# Orion-Tr DC-DC converters isolated: 100 Watt series

[www.energiainnovadora.com](http://www.energiainnovadora.com)



**Orion-Tr 12/24-5 (120W)**



**Orion-Tr 12/24-5 (120W)**

### Remote on-off

The remote on-off eliminates the need for a high current switch in the input wiring. The remote on-off can be operated with a low power switch or by for example the engine run/stop switch (see manual).

### Adjustable output voltage: can also be used as a battery charger

For example to charge a 12 Volt starter or accessory battery in an otherwise 24 V system.

### All models are short circuit proof and can be paralleled to increase output current

An unlimited number of units can be connected in parallel.

### IP43 protection

When installed with the screw terminals oriented downwards

### Screw terminals

No special tools needed for installation

### Input fuse

On 12V and 24V input models only

Isolated converters	Orion-Tr 12/12-9 (110 W)	Orion-Tr 12/24-5 (120 W)	Orion-Tr 24/12-9 (110 W)	Orion-Tr 24/24-5 (120 W)	Orion-Tr 24/48-2,5 (120 W)	Orion-Tr 48/12-9 (110 W)	Orion-Tr 48/24-5 (120 W)	Orion-Tr 48/48-2,5 (120 W)
Input voltage range	8-17V	8-17 V	16-35 V	16-35 V	16-35 V	32-70 V	32-70 V	32-70 V
Under voltage shut down	7 V	7 V	14 V	14 V	14 V	28 V	28 V	28 V
Under voltage restart	7,5 V	7,5 V	15 V	15 V	15 V	30 V	30 V	30 V
Nominal output voltage	12,2 V	24,2 V	12,2 V	24,2 V	48,2 V	12,2 V	24,2 V	48,2 V
Output voltage adjust range	10-15 V	20-30 V	10-15 V	20-30 V	30-60 V	10-15 V	20-30 V	30-60 V
Output voltage tolerance	+/- 0,2 V	+/- 0,2 V	+/- 0,2 V	+/- 0,2 V	+/- 0,2 V	+/- 0,2 V	+/- 0,2 V	+/- 0,2 V
Output noise	2 mV rms	2 mV rms	2 mV rms	2 mV rms	2 mV rms	2 mV rms	2 mV rms	2 mV rms
Cont. output current at nominal output voltage and 25°C	9 A	5 A	9 A	5 A	2,5 A	9 A	5 A	2,5 A
Maximum output current (10 s) at nominal output voltage	12,5 A	6,3 A	12,5 A	6,3 A	3,0 A	12,5 A	6,3 A	3,0 A
Short circuit output current	32 A	23 A	39 A	30 A	19 A	27 A	25 A	17 A
Cont. output power at 25°C	110 W	120 W	110 W	120 W	120 W	110 W	120 W	120 W
Cont. output power at 40°C	85 W	110 W	85 W	115 W	115 W	85 W	100 W	85 W
Efficiency	87%	88%	85%	87%	88%	87%	86%	89%
Galvanic isolation	200 V dc between input, output and case							
Operating temperature range	-20 to +55°C (derate 3% per °C above 40°C)							
Humidity	Max. 95% non condensing							
DC connection	Screw terminals							
Maximum cable cross-section	6 mm <sup>2</sup> AWG10							
Weight	0,42 kg							
Dimensions h x w x d	100 x 113 x 47 mm							
Standards: Safety Emission Immunity Automotive Directive	EN 60950 EN 61000-6-3, EN 55014-1 EN 61000-6-2, EN 61000-6-1, EN 55014-2 EN 50498							